

# toner

: 5A ? ]h

## 1 GHz FAM Series 5hYbi Urcf DUXg

### FAM-Kit

The FAM Kit is a selection of 10 each of the Toner FAM Series

SF type in line attenuators in the following values: 1, 2, 3, 6, 8, 10, 12, 16 & 20 dB.

Y a@C@ A aA [ ^ A a|A, æ • A@e^ A@ &| !!^ &Aæ } ~ æ| !•  
[ ] A@e aA| Aab • Aã } æ • A@e A ^^a^aÈV@ Aæ } ~ æ| !• A  
æ^ A Aã \*^ aA Aã A Aã FÈD A| æ cA d | æ ^ A| cA@e A  
^æ !^ • Aæ &^ æ Aã A [ A [ ^ Aæ A ^^ A@ &| } c) • ÈV@ A  
à [ cA@e A F&| { ] æ d ^ } • Aæ aAã } æ &| • ^ Aã A| A  
• ^ & !^ A@ A@e F Aæ } ~ æ| !• È



### SPECIFICATIONS

MODEL	FAM-1	FAM-2	FAM-3	FAM-6	FAM-8	FAM-10	FAM-12	FAM-16	FAM-20
<b>ATTENUATION (dB)</b>									
5-600 MHz	0.9	2.2	2.7	5.6	7.5	9.6	11.5	15.8	19.4
600-750 MHz	1.0	2.1	3.4	6.3	8.2	10.6	12.5	16.5	19.8
750-900 MHz	1.1	2.2	3.4	6.3	7.8	10.6	12.5	16.5	19.3
900-1000 MHz	1.1	2.3	2.5	5.5	7.4	10.3	11.7	15.7	18.8
<b>RETURN LOSS</b>									
<b>(dB) minimum</b>									
5-600 MHz	24	23	23	26	26	22	22	26	20
600-750 MHz	22	21	21	24	22	21	21	22	19
750-900 MHz	18	18	20	22	20	20	20	20	18
900-1000 MHz	18	18	18	18	18	18	18	18	17