

DEVISER Signal Level Meter
Model# DS2003R

Frequency

Range: 5 MHz - 1000 MHz
Frequency Step: 50 kHz, 100 kHz, 1 MHz, 10 MHz and 100 MHz

Level Measurement

Range: -30 dBmV to 60 dBmV (30 dBuV to 120 dBuV)
Accuracy: ± 2 dB (20 °C \pm 5 °C)
Resolution: 0.5 dB
Digital Power Range: -20 dBmV to 50 dBmV (40 dBuV to 110 dBuV)

Mechanical

Dimensions: 6.2" x 2.8" x 1.6" (168 mm x 71 mm x 42 mm)
Weight: 13 oz (368 g) (with battery)
Operating Temperature Range: 0° - 105° F (-10° - 40° C)
Audio: Built-in speaker (Auto on in single frequency mode)
Power Supply / Charger: 3.6 V / 2.1 AH Ni-MH
Battery (Rechargeable): 3.6 V / 2.5 AH Ni-MH
Working Time Approximately 4-6 Hours